

60/120 Watt Commercial Mixer Amplifier

A-60/A-120



OVERVIEW

The A-60/A-120 is a simple and economical multi-purpose desk top mixer-amplifier providing a cost-effective solution to public address and similar applications. Two versions are available with outputs of 60 and 120 watts respectively into direct (4 ohms) or distributed (70V/100V line) speaker systems. Each has five inputs; three microphone, balanced, low impedance and two auxiliary, unbalanced, high impedance. Microphone one has selectable vox priority over all other inputs. Bass and treble tone controls are provided. The A60/120 amplifier is designed for reliable service in permanent installations, and comes complete with short-circuit and thermal protection and is ideal for voice reproduction and BGM applications.

FEATURES

- **High Power, Low Distortion**
(60W (A-60) or 120W (A-120) of RMS power, with less than 1% THD.)
(transformer coupled)
- **Versatile and Easy to Use**
- **3 Mic inputs (combi XLR / 1/4" jack)**
- **2 AUX inputs (stereo phono)**
- **Priority Muting (Mic1 input mutes other inputs when in use.)**
- **Flexible Design (Mono 4Ω or 70V/100V High-Impedance Outputs.)**
- **Phoenix screw terminals for loudspeaker connection**
- **Tone Control (Separate Bass and Treble controls to tailor your sound.)**
- **Optional Rack mount Kit (2U) (BKT-A120 Bracket)**

SPECIFICATIONS

		A-60	A-120
Rated Output/Impedance		15.5V/4Ω, 70V/81.6Ω, 100V/166.7Ω	21.9V/4Ω, 70V/40.8Ω, 100V/83.3Ω
Frequency Response (±3dB)		80Hz~16kHz	
T.H.D.		Less than 1%	
S/N	Mic	Better than 50dB	
	Aux	Better than 75dB	
Input Sensitivity/Impedance	Mic Input 1~3	-60dB/600Ω, Bal	
	Aux 1 Input	-10dB/10kΩ, Unbal	
	Aux 2 Input	+3dB/10kΩ, Unbal	
Tone Control	Treble (10kHz)	±12dB	
	Bass (100Hz)	±12dB	
Power Source		100~120VAC or 220~240VAC; 50/60Hz (Supplied AC mains transformer depends on country requirements)	
Power Consumption		75W	105W
Weight (Set)		8.9kg/19.6lb	10.3kg/22.7lb
Dimensions (Set)		420(W) x 88(H) x 320(D)mm/16.5(W) x 3.5(H) x 12.6(D)in	

* Specifications and design are subject to change without notice.

60/120 Watt Commercial Mixer Amplifier


A-60/A-120




APPLICATION

Our technology can be found in schools, hospitals, malls, campus, transportation, correctional facilities and a variety of commercial and industrial applications.

The A-60/120 series amplifiers are ideal solutions for installations in restaurants, retail stores, classrooms, meeting rooms or anywhere voice reproduction and BGM is required.



BLOCK DIAGRAM



Inter-M Corporation

- **Office** : 653-5 BANGHAK-DONG, DOBONG-GU, SEOUL, KOREA
 - **Tel** : +82-2-2289-8140~8, Fax : +82-2-2289-8149
 - **Home page**: <http://www.inter-m.com>, **E-mail**: overseas@inter-m.com

Inter-M Corporation (USA)

- **Office** : 14730 E. FIRESTONE BLVD #312 LA MIRADA, CA 90638
 - **Tel** : +1-714-523-1870, Fax : +1-714-523-1882
 - **Home Page** : <http://www.inter-m.net>, **E-mail** : info@inter-m.net