

110 Series Mini Bullet 1080p Analog Surveillance Camera

> Quick-Start Guide

Box Contents

- Camera
- Mounting template
- 4 wall anchors
- 3mm hex wrench
- CC tester cable

You must provide:

- Phillips screwdriver
- Power source: 12V DC
- CC-TV tester (recommended)



Inspection

Ensure that the device is in good condition and all parts are included. If the product does not work properly, contact technical support. Do not disassemble the camera for repair or maintenance.


We recommend installing with RJ59 or RJ6 cabling with two-wire power (regular or siamese). This provides better performance over distance than category cable with baluns.



WARNING: This product can expose you to chemicals including cadmium, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov.

Overview

Before installing, familiarize yourself with the parts of your camera.





Prepare for Installation


For your safety:

- Power off all equipment during installation.
- Ensure the wall is strong enough to hold three times the weight of the camera and the mount.
- If the mounting surface is cement, use the included expansion screws to install the camera. If mounting to a wood surface, use self-tapping wood screws (not included) to secure the camera.

Install the Camera

- 1. Drill a cable hole and pilot holes for your screws in the ceiling, using the supplied template.
- 2. Route the cables through the cable hole.
- 3. Secure the base of the camera to the ceiling.
- 4. This camera has an elbow joint and two rotary joints for perfect aim. Loosen the two Phillips screws and the thumb lock at the camera's base.
- 5. Adjust the angle of the elbow as desired, and tighten the elbow screw, A.
- 6. Rotate the camera so that it faces in the proper direction, and tighten the base lock, B.
- 7. Spin the camera casing so that the picture is level, and tighten the level Phillips screw, C.
- 8. Connect the power and video cables.





Note that this camera has an OSD menu that can be accessed through your DVR web interface.

Support

866-838-5052 or TechSupport@SnapAV.com

5-Year Limited Warranty

This Luma Surveillance™ product has a 5-Year Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products that have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to a designated service center with an assigned return authorization (RA) number. Contact technical support for an RA number.

Copyright ©2015–2019 by SnapAV. All rights reserved. SnapAV, Luma Surveillance, and all related marks and images are trademarks or registered trademarks of SnapAV.

Version 181204-1554