Public Address Amplifier

A-60/120



PUBLIC ADDRESS AMPLIFIER



OVERVIEW

A-60/120 are Public Address Amplifiers that can be used in those places in need of playing BGM or sound amplified such as classrooms, educational institutions, restaurants, and cafes.

It has three MIC inputs and two AUX input terminals that are capable of inserting exterior signals like CD and Deck.

A-Series is designed with MIC priority function and to adjust between Bass and Treble for customer's needs and wants.

FEATURES

HIGH POWER, LOW DISTORTION

60W (A-60) or 120W (A-120) of RMS power, with less than 1% THD.

• VERSATILE AND EASY TO USE

Three Mic inputs, two Aux Inputs.

PRIORITY MUTING

Mic1 input mutes other inputs when in use.

• FLEXIBLE DESIGN

Mono 4Ω or 70V/100V High-Impedance Outputs.

• TONE CONTROL

Separate Bass and Treble controls to tailor your sound.










Cafe and Lobby

Classroom


Kindergarten

Amusement Park





IMPEDANCE INSTALLATION RECOMMENDED AMPLIFIER + SPEAKER BLOCK DIAGRAM





		A-60	A-120
Rated Output/Impedance		15.5V/4Ω, 70V/81.6Ω, 100V/166.7Ω	21.9V/4 , 70V/40.8 , 100V/83.3
Input Sensitivity/Impedance	MIC 1-3	-60dB/600Ω, BAL	
	AUX 1	-10dB/10kΩ, UNBAL	
	AUX 2	+3dB/10kΩ, UNBAL	
T.H.D.		Less than 1%	
Frequency Response (±3dB)		80Hz~16kHz	
S/N	MIC	Better than 50dB	
	AUX	Better than 75dB	
Tone Control	HIGH (10kHz)	±12dB	
	LOW (100Hz)	±12dB	
Power Source		AC 220V/60Hz	
Power Consumption		75W	105W
Weight		8.9kg / 19.6lb	10.3kg / 22.7lb
Dimensions (W×H×D)		420×88×320mm / 16.5×3.5×12.6in	

