

Programmable IR/RF Remote Control with 1.5" LCD



OVERVIEW

Programmable handheld remote provides single-room IR control – TV, A/V components, cable and satellite boxes. It is ideal for home theater installations, kitchens and bedrooms. The 1.5" color LCD screen displays up to 48 devices (up to eight pages per device for a total of 384 pages). When used with a compatible Complete Control base station, the MX-780 controls integrated A/V components through walls and cabinet doors, or even from outside. There is no need to point the remote control at the components or even be in the same room.

- Handheld remote with 1.5" color LCD screen
- Displays up to six buttons per screen
- Delivers single-room, one-way control of IR devices
- Operates on standard AA alkaline batteries
- MX-780i features 433 MHz frequency for international and highly-populated markets

HIGHLIGHTS

IR Range 30-50 feet

IR Frequency 15 kHz to 460 kHz

RF Range 50-100 feet

RF Frequency 418 MHz (MX-780), 433 MHz (MX-780i)

Power AA alkaline batteries

SPECIFICATIONS

SKU	MX-780, UPC 656787-207806 / MX-780i, UPC 656787-278011
System	Complete Control™ - Professional programming required
In the Box	Handheld remote, four AA alkaline batteries
Dimensions	2.2" W x 8.7" H x 1.3" D
Weight	.5 lbs. with batteries
Warranty	1 year limited USA warranty



914.705.4148







